

Lähetävän Burrel-riistakameran asennusohje.

Varmista ensimmäiseksi, että kameraan tulevan liittymän SIM-kortista on poistettu PIN koodin kysely.

Jos lähetät kuvia sähköpostiin varmista matkapuhelimella, että liittymän internet-yhteys toimii.

Jos lähetät kuvia kuvaviestinä puhelimeen varmista matkapuhelimella, että liittymällä voi lähettää kuvaviestejä. Varmistus tapahtuu lähettämällä kuvaviesti puhelimesta toiseen.

1. Sijoita SIM- ja muistikortti kameraan ja valitse kieleksi suomi.
2. Valitse lähetysasetuksista kohta asetustyökalu->jatka. Valinnan jälkeen kamera ilmoittaa ladanneensa työkalun muistikortille.
3. Kytke muistikortti tai kamera tietokoneeseen ja avaa ulkoiselta asemalta WIRELESS-ohjelma.
4. Täytä WIRELESS-ohjelman ikkunat liittymäsi asetusten mukaisesti (katso kuvat alta).
5. Jos halutaan käyttää riistakameran etäkäskyä, tulee numero josta käskyjä lähetetään olla kohdassa phone1.
SMS Control kohdassa tulee olla valittuna vaihtoehto ON.
6. Valitse ohjelmasta kohta Save. Valinnan jälkeen ohjelma tallentaa MMSCFG-nimisen tiedoston muistikortille ohjelman kuvakkeen viereen.
7. Käynnistä kamera Setup-tilaan ja valitse lähetysasetukset kohdasta päivitä asetukset->jatka. Valinnan jälkeen kamera päivittää operaattoriasetukset kameraan.
8. Halutessasi voit tarkistaa sähköposti->jatka kohdasta, että ohjelmoimasi sähköpostiosoite on oikein.

Saunalahti dataliittymä

Huom! 14, 15 ja 16 –sarjanumeroalkuiset Saunalahden SIM-kortit käyttävät Elisan asetuksia.

The image displays the 'Wireless Camera Setup v2.3' software interface, which is divided into several sections for configuring the camera's communication settings. The 'Email Setting' window is open, showing fields for Email Provider (Other), Account (burrel@netti.fi), Password (*****), Re-Type Password (*****), SMTP Server (posti.saunalahti.fi), and SMTP Port (25). The 'Operator Parameter' window is also open, showing fields for Internet APN (internet.saunalahti), Username, Password, MMS APN (mms.saunalahti.fi), Username, Password, URL (MMSC) (http://mms.saunalahti.fi:8002), Gateway (Proxy) (62.142.4.197), and Port (8080). The main 'Wireless Camera Setup v2.3' window shows the 'Send Mode' (Instant, Daily Report, Off), 'Send Via' (MMS, Internet), 'Operator Parameter' (Country, Operator), 'Send To' (Phone, Both, Email, Other), 'Recipients' (Phone1, Phone2, Phone3, Phone4, Email 1, Email 2, Email 3, Email 4), 'Image' (Max Image Size, Image From), and 'SMS' (SMS Control, Status Response) sections. Arrows indicate the flow from the 'Email Setting' window to the 'Email Setting' field in the 'Send Via' section, and from the 'Operator Parameter' window to the 'Operator Parameter' field in the 'Send Via' section.

Wireless Camera Setup v2.3

Send Mode

- ☒ Instant Max Num: 50
- ☐ Daily Report 21 : 30
- ☐ Off

Send Via

- ☐ MMS
- ☒ Internet **Email Setting ...**

Operator Parameter

Country: Custom

Operator: Custom **Parameters ...**

Send To

- ☐ Phone ☐ Both
- ☒ Email
- ☐ Other

Recipients

- ☐ Phone1
- ☐ Phone2
- ☐ Phone3
- ☐ Phone4
- ☒ Email 1 asiakkaan s.posti
- ☐ Email 2
- ☐ Email 3
- ☐ Email 4

Image

Max Image Size: 200 KB Image From: OFF

SMS

SMS Control: OFF ☐ Status Response

Email Setting

Email Provider: Other

Account (@xxx): burrel@netti.fi (keksitty)

Password: ***** burrel (keksitty)

Re-Type Password: ***** burrel (keksitty)

SMTP Server: posti.saunalahti.fi

SMTP Port: 25 ☐ SSL

Operator Parameter

Internet

APN: internet.saunalahti

Username:

Password:

MMS

APN: mms.saunalahti.fi

Username:

Password:

URL(MMSC): http://mms.saunalahti.fi:8002

Gateway(Proxy): 62.142.4.197

Port: 8080

Sonera ja Tele Finland asetukset.

HUOM! Jos kuvia lähetetään sähköpostiin on käytössä oltava opengate-lisäpalvelu.

The main window is titled "Wireless Camera Setup v2.5". It contains several sections for configuring the camera's communication settings.

Send Mode: Includes radio buttons for "Instant", "Daily Report", and "Off". The "Instant" mode has a "Max Num" field set to 50. The "Daily Report" mode has fields for "21" and "30".

Send Via: Includes radio buttons for "MMS" and "Internet". The "Internet" option is selected, and there is a button labeled "Email Setting ...".

Operator Parameter: Includes dropdown menus for "Country" and "Operator", both set to "Custom". There is a button labeled "Parameters ...".

Send To: Includes radio buttons for "Phone", "Both", "Email", and "Other". The "Email" option is selected.

Recipients: Includes checkboxes for "Phone1", "Phone3", "Email1", and "Email3". "Phone1" and "Email1" are checked. The "Email1" field contains "asiakkaan s.posti".

MMS/GPRS Image: Includes a dropdown for "Image Quality" set to "Normal" and a field for "Image From".

SMS: Includes a dropdown for "SMS Control" set to "OFF" and a checkbox for "Status Response".

At the bottom are buttons for "Default", "Load ...", "Save", and "Cancel".

Email Setting (Sub-window): This window is titled "Email Setting". It includes a dropdown for "Email Provider" set to "Other". The "Account (@xxx)" field contains "burrel@netti.fi (keksitty)". The "Password" and "Re-Type Password" fields both contain "***** burrel (keksitty)". The "SMTP Server" field contains "mail.inet.fi". The "SMTP Port" field contains "25". There is an unchecked checkbox for "SSL". At the bottom are "OK" and "Cancel" buttons.

Operator Parameter (Sub-window): This window is titled "Operator Parameter". It includes a section for "Internet" with an "APN" field set to "opengate", and empty fields for "Username" and "Password". It also includes a section for "MMS" with an "APN" field set to "mms", and empty fields for "Username" and "Password". The "URL(MMSC)" field contains "http://mms.sonera.fi:8002". The "Gateway(Proxy)" field contains "195.156.25.33". The "Port" field contains "8080". At the bottom are "OK" and "Cancel" buttons.

DNA/ DNA prepaid

Email setting kohdassa account ja password ovat keksittyjä. Näihin ei kannata laittaa olemassa olevaa sähköpostia.

The screenshot displays the 'Wireless Camera Setup v2.5' application window. The 'Email Setting' dialog box is open, showing fields for 'Email Provider' (set to 'Other'), 'Account' (kamera@netti.fi), 'Password' (*****), 'Re-Type Password' (*****), 'SMTP Server' (smtp.dna044.com), and 'SMTP Port' (25). The 'Send Via' section in the main window is set to 'Internet', and the 'Email Setting...' button is highlighted. The 'Recipients' section shows 'Phone1' and 'Email 1' checked. The 'MMS/GPRS Image' section shows 'Image Quality' set to 'Normal'. The 'SMS' section shows 'SMS Control' set to 'OFF'. The 'Operator Parameter' dialog box is also open, showing fields for 'APN' (internet), 'Username', 'Password', 'URL(MMSC)' (http://mms.dnainland.fi), 'Gateway(Proxy)' (10.1.1.1), and 'Port' (8080).

Elisa Dataliittymä

Email setting kohdassa account ja password ovat keksittyjä. Näihin ei kannata laittaa olemassa olevaa sähköpostia. Elisan smtp.kolubus.fi serveri ei vaadi todellista sähköpostia.

Wireless Camera Setup v2.8

Send Mode

☒ Instant Max Num

☐ Daily Report :

☐ Off

Send Via

☐ MMS

☒ Internet [Email Setting ...](#)

Operator Parameter

Country

Operator [Parameters ...](#)

Send To

☐ Phone ☐ Both

☒ Email

☐ Other

Recipients

☒ Phone1 ☐ Phone2

☐ Phone3 ☐ Phone4

☒ Email 1 ☐ Email 2

☐ Email 3 ☐ Email 4

MMS/GPRS Image

Image Quality Image From

SMS

SMS Control ☐ Status Response

[Default](#) [Load ...](#) [Save](#) [Save as...](#) [Cancel](#)

Email Setting

Email Provider

Account (@xxx)

Password

Re-Type Password

SMTP Server

SMTP Port ☐ SSL

[OK](#) [Cancel](#)

Operator Parameter

Internet

APN

Username

Password

MMS

APN

Username

Password

URL(MMSC)

Gateway(Proxy)

Port

[OK](#) [Cancel](#)